OPERATOR'S MANUAL






PCB CONECTOR JAMMA

	1	1				
SOLDER SIDE			COMPONENTS SIDE			
GND	A	1	GND			
GND	В	2	GND			
+ 5V	С	3	+ 5V			
+ 5V	D	4	+ 5V			
N.C.	Е	5	N.C.			
+ 12V	F	6	+ 12V			
	Н	7				
COIN COUNTER 2	J	8	COIN COUNTER 1			
(COIN LOCK OUT 2)	K	9	(COIN LOCK OUT1)			
SPEAKER (-)	L	10	SPEAKER (+)			
N.C.	М	11	N.C.			
VIDEO GREEN	N	12	VIDEO RED			
VIDEO SYNC	Р	13	VIDEO BLUE			
SERVICE SW	R	14	VIDEO GND			
N.C.	S	15	TEST SW			
COIN 2	Т	16	COIN 1			
2P START	U	17	1P START			
2P UP	V	18	1P UP			
2P DOWN	w	19	1P DOWN			
2P LEFT	X	20	1P LEFT			
2P RIGHT	Y	21	1P RIGHT			
2P SHOT	Z	22	1P SHOT			
2P BOMB	а	23	1P BOMB			
N.C.	b	24	N.C.			
N.C.	С	25	N.C.			
N.C.	d	26	N.C.			
GND	е	27	GND			
GND	f	28	GND			

HOW TO OPERATE







CONTROL STICK

ОТ ВОМВ

MONITOR	HORIZONTAL
GAME STYLE	1 PLAYER o 2 PLAYERS Simultáneos

POSITIONS OF DIP SW

SW2 SW1

	SW1			1	2	3	4	5	6	7	8
1	COIN	1	CREDIT	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
1	COIN	2	CREDITS	ON	OFF	OFF	OFF	ON	OFF	OFF	OFF
1	COIN	3	CREDITS	OFF	ON	OFF	OFF	OFF	ON	OFF	OFF
1	COIN	4	CREDITS	ON	ON	OFF	OFF	ON	ON	OFF	OFF
1	COIN	5	CREDITS	OFF	OFF	ON	OFF	OFF	OFF	ON	OFF
1	COIN	6	CREDITS	ON	OFF	ON	OFF	ON	OFF	ON	OFF
2	COINS	1	CREDIT	OFF	ON	ON	OFF	OFF	ON	ON	OFF
3	COINS	1	CREDIT	ON	ON	ON	OFF	ON	ON	ON	OFF
4	COINS	1	CREDIT	OFF	OFF	OFF	ON	OFF	OFF	OFF	ON
5	COINS	1	CREDIT	ON	OFF	OFF	ON	ON	OFF	OFF	ON
2	COINS	3	CREDITS	OFF	ON	OFF	ON	OFF	ON	OFF	ON
	FREE PLAY		ON	ON	ON	ON	ON	ON	ON	ON	
				COIN 1					COI	V 2	

SW2		1	2	3	4	5	6	7	8
	NORMAL	OFF	OFF						
DIFFICULTY	HARD	OFF	ON						
LEVEL	EASY	ON	OFF						
	HARDEST	ON	ON						
NUMBER	3			OFF	OFF				
OF	2			OFF	ON				
PLAYERS	1			ON	OFF				
ADVERTIS	E YES					OFF			
SOUND	NO					ON			
GIRLS	HARD						OFF		
GINLS	LIGHT						ON		
TEST	NO								OFF
1231	YES								ON

